

## HSA-75/1+1 M

- Surge arresters type T2+T3 ensure the equipotential bonding and reduce switching, induced and residual overvoltage in LV power supply systems.
- The products consist of varistors with big discharge ability.
- Configurations 1+1 and 3+1 are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Installed at the boundaries of LPZ 1 LPZ 3 into subsidiary switchboards and control panels.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- S indication specifies a version with remote monitoring.

Туре		HSA-75/1+1 M
Test class according to EN 61643-11:2012 (IEC 61643-11:2011)		T2, T3
System		TN-S, TT
Number of poles		2
Rated operating AC voltage	U <sub>N</sub>	60 V
Maximum continuous operating voltage AC	Uc	75 V
Maximum discharge current (8/20)	I <sub>max</sub>	40 kA
Nominal discharge current for class II test (8/20)	l <sub>n</sub>	15 kA
Open circuit voltage of the combination wave generator	U <sub>oc</sub>	6 kV
Total discharge current (8/20) L+N->PE	I <sub>Total</sub>	50 kA
Voltage protection level at In (L/N)	Up	< 0.45 kV
Voltage protection level at In (N/PE)	Up	< 1.3 kV
Voltage protection level at U <sub>oc</sub> (L/N)	Up	< 0.3 kV
Impulse discharge current for class I test (10/350) N/PE	I <sub>imp</sub>	20 kA
Temporary overvoltage test (TOV) for $t_T = 5 s (L/N)$	U <sub>T</sub>	91 V
Temporary overvoltage test (TOV) for $t_T = 120 \text{ min (L/N)}$	U <sub>T</sub>	104 V
Temporary overvoltage test (TOV) for $t_T = 0.2 \text{ s} (N/PE)$	U <sub>T</sub>	1 200 V
Response time (L/N)	t <sub>A</sub>	< 25 ns
Response time (N/PE)	t <sub>A</sub>	< 100 ns
Maximal back-up fuse		160 A gL/gG
Residual current	I <sub>PE</sub>	≤ 5 μA
Short-circuit current rating at maximum back-up fuse	I <sub>SCCR</sub>	60 kA <sub>rms</sub>
Follow current interrupt rating (N/PE)	l <sub>fi</sub>	0.1 kA <sub>rms</sub>
Lightning protection zone		LPZ 1-2, LPZ 2-3
Housing material		Polyamid PA6, UL94 V-0
Degree of protection		IP20
Operating temperature	θ	-40 ÷ 70 °C
Humidity range	RH	5 ÷ 95 %
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2	S	2.5 mm² (L, N) 6 mm² (PE, PEN)



mp fastening range (solid conductor)       Imp fastening range (stranded conductor)       Imp fastening range (stranded conductor)         mp fastening moment       Imp fastening moment       Imp fastening moment         allation       Imp fastening moment       Imp fastening moment         allation       Imp fastening moment       Imp fastening moment         dular width       Imp fastening moment       Imp fastening moment         dular dep position       Imp fastening moment       Imp fastening moment         dular dep fasten environment       Imp fastening moment       Imp fastening         note signalling       Imp fastening       Imp fastening         fourtance of local signaling       Imp fastening       Imp fastening         foular design       Imp fastening to standards       Imp fastening         signed according to standards       Imp fastening       Imp fastening         suprements and test methods for SPDs connected to low-voltage power systems       Imp fastening         suprements and test methods for SPDs connected to low-voltage power syst	1.5 ÷ 25 mm <sup>2</sup> 1.5 ÷ 16 mm <sup>2</sup> 3 Nm On DIN rail 35 mm 2 TE Any Internal Optic OK – clear target
htening moment allation () dular width erating position duct placement environment nalling at the device nortance of local signaling note signalling dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials oblication standards	3 Nm On DIN rail 35 mm 2 TE Any Internal Optic
allation dular width erating position duct placement environment duct placement environment nalling at the device of local signaling note signalling duct design cle number of spare module dular design cle number of spare dular duar duar duar duar duar duar duar du	On DIN rail 35 mm 2 TE Any Internal Optic
dular width       Image: Constraint of the second of the sec	2 TE Any Internal Optic
erating position duct placement environment nalling at the device nortance of local signaling mote signalling dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials blication standards	Any Internal Optic
duct placement environment nalling at the device ortance of local signaling mote signalling dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials	Internal Optic
nalling at the device       Image: Sector and a constraints         note signalling       Image: Sector and a constraints         dular design       Image: Sector and a constraints         cle number of spare module       Image: Sector and a constraints         time       Image: Sector and test methods for SPDs connected to low-voltage power systems         sety of Flammability of Plastic Materials       Image: Sector and a constraints	Optic
anote signalling mote signalling dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials blication standards	•
note signalling dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials	OK – clear target
dular design cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials blication standards	FAULT – red target
cle number of spare module time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials blication standards	No
time signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials plication standards	Yes
signed according to standards quirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials plication standards	27 190
auirements and test methods for SPDs connected to low-voltage power systems ety of Flammability of Plastic Materials plication standards	> 100 000 h
ety of Flammability of Plastic Materials	
olication standards	IEC 61643-11:2011
	UL 94
	IEC 62305:2010
ection and erection of electrical equipment – Switchgear and controlgear	HD 60364-5-53:2022
ection and application principles for SPDs connected to low-voltage power systems	CLC/TS 61643-12:2009
lering, packaging and additional data	
ss m	188 g
ss (including the packaging) m	202 g
kaging dimensions (H x W x D)	45 x 102 x 74 mm
kaging value V	0.34 dm <sup>3</sup>
M group	EG000021
M class	EC000941
stoms tariff no.	85363010
N code	8590681116258
number	0090001110200




The link in the QR code leads to the online presentation of the HSA-75/1+1 M. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials.

For more information, visit www.hakel.com






## Application wiring diagram (installation)



## Internal diagram



HSA-75/1+1 M – **page 3/3** Datasheet generated on 2024-04-24 21:21:43