

TL 400T

- The coupling devices TL* are used to adapt the input circuits of the insulation monitoring device to a higher operating voltage than the operating voltage of the IMD directly.
- The coupling units are connected between IT power supply system and insulation monitoring device.

| Туре | | TL 400T |
|--|-----------------|--|
| Rated operating AC voltage | U_N | 400 V |
| Maximum continuous operating voltage AC | U _c | 500 V |
| Designed for insulation monitoring device | | HIS71, HIG95, HIG93, HIG91, HIG92, HIG94 |
| Maximal operating current AC | I _c | < 3 x 0,1 mA |
| Internal resistance | R _{IN} | 3 x 12,7 kΩ |
| Internal inductance | L _{IN} | 3 x 330 H |
| Offset for insulation monitoring device | R_{tlext} | 4.4 kΩ |
| Housing material | | Polyamid PA6, UL94 V-0 |
| Degree of protection | | IP20 |
| Operating temperature | θ | -25 ÷ 55 °C |
| Recommended cross-section of connected conductors | S | 1.5 mm ² |
| Tightening moment | | 0,2 Nm |
| Installation | | On DIN rail 35 mm |
| Modular width | | 2 TE |
| Operating position | | Any |
| Operation type | | Permanent |
| Lifetime | | > 100 000 h |
| Use for traction | | Yes |
| Designed according to standards | | |
| Insulation coordination for equipment within low-voltage systems | | IEC 60664-1:2007 |
| Safety of power transformers, power supplies, reactors and similar | | IEC 61558-1:2005 |
| Ordering, packaging and additional data | | |
| Mass | m | 310 g |
| Mass (including the packaging) | m | 324 g |
| Packaging dimensions (H x W x D) | | 45 x 102 x 74 mm |
| Packaging value | V | 0.34 dm ³ |
| Customs tariff no. | | 90303370 |
| EAN code | | 8590681110744 |
| Art. number | | 70 514 |

Coupling devices for insulation monitoring devices






The link in the QR code leads to the online presentation of the **TL 400T**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com**



Application wiring diagram (installation)



Internal diagram

